

4 PRONG UNIT

Be protected in minutes

The #1 cause of structure fires in the U.S. is cooking! These fires are responsible for an average of 1 billion dollars in damage each year. FireAvert helps mitigate your risk of having a kitchen fire. Simply plug FireAvert in behind the stove and sync it to the nearest smoke alarm. In the event the smoke alarm sounds due to the stove/oven, FireAvert will cut power, eliminating the heat source to prevent a kitchen fire! **See video below.**



Features

- Works with any smoke detector sound
- No batteries and maintenance free
- No professional install needed
- Fits in the void space behind most electric stoves
- Electrical Current Detection causes activation only when stove is on and smoke alarm sounds
- Reusable with a 25 year expected life.
- Resets at the electrical panel
- 3 and 4 prong configurations available
- Light indicates number of times activated
- Sound detection of smoke alarm from up to 60



4 Prong | A-E04-14-50



[SEE HOW EASY IT IS TO INSTALL](#)

Installation Process

FireAvert is plug-n-play ready. Simply plug it into the back of the stove. FireAvert is activated by the smoke alarm, cutting power to the stove and oven when the smoke alarm is sounding. To reset the stove after it cuts off power simply flip the stove breaker off and then back on again. This will enable your stove to begin working again.

4 PRONG UNIT

Electrical Specifications

Operating Voltage	125/250v
Amperage	40 amps 60Hz
Plug Configuration	NEMA 14-50 R/P
Pole	3
Wire	4 wire grounding
Fire Rating	Housing ABS fire retardant - UL94(5Va,V-0,V-1,V-2,HB)

Physical Specifications

Master Carton Dimensions	14 inches wide x 18 inches high x 22.5 inches long
Master Carton Weight	40 lbs
Dimensions	7 ¾ inches (20 cm) x 2 ½ inches (6.35 cm) x 3 5/8 inches (9.2 cm) – (LxWxH)
Weight	1 ½ LB (0.68 Kg)
Color	Black
Operating Temperature Range	32°F to 90°F (0°C to 33°C)
Operating Humidity Range	0 to 80% RH non-compensating
Mounting	None required. Plugs directly into NEMA 14-50R outlet for electrical
Stove/Ranges	Electric, 240v
Environmental	RY PB Free

LED Modes

LED Mode	White LED	Green LED	Red LED
Power Up	Flash	Off	Flash (Cut Count)
Standby	Off	Solid	Off
Protection Mode	Off	Off	Solid

Certifications

UL 498A Certification | CSA 22.2 Certification | FCC Certification



Warranty

[CLICK HERE](#) to download the FireAvert Warranty